

Common Logger32 soundcard macros

Macro	Action
\$transmit\$	Start transmitting the TX buffer
\$receive\$	End transmission, go to receive
\$call\$	Callsign of the guy I am working from the log entry window
\$myCall\$	My callsign (reset by right click in entry field → Change operator)
\$name\$	Name of the guy I am working from the log entry window
\$sentRST\$	RST of the guy I am working from the log entry window
\$receivedRST\$	RST he sent me, from the log entry window
\$receivedGrid\$	Locator he sent me, from the log entry window
\$longDate\$	UTC date as dd-mm-yyyy e.g. 31-12-2012
\$longTime\$	UTC time as hh:mm:ss e.g. 02:33:54
\$longDateAndTime\$	UTC date & time as dd-mm-yyyy hh:mm:ss
\$mode\$	Current mode from log entry window
\$band\$	Current band, taken from the log entry window
\$loop\$	Wait a few seconds then repeat this memory (escape or start entering call info to stop it repeating; use another \$loop\$ for longer delay between repeats)
\$serialNumber\$	Serial number from # field in lower status bar (reset using # button)
\$log\$	Complete a QSO, writing the QSO info to the log and clearing the log entry form ready for the next
\$MMVARImode06\$	Change to PSK31 mode
\$MMVARImode09\$	Change to RTTY mode